



# JB16 Jumper Bars

## Terminal Blocks Accessories



### Features and Benefits

Insulated jumper bar with screw mounting.

### Main Technical Data

	IEC	cULus - CSA	Ex e
Rated current	110 A	150 A	
Rated voltage Standard use	1000 V	600 V	630 V
Alternated poles	400 V	300 V	Not authorized
Impulse withstand voltage	8000 V		
Protection	IP 20	NEMA 1	

### Mounting Instructions

Screw

Tool		Flat screwdriver Ø 5.5 mm Ø 0.217 in
Torque		1.2 Nm ± 0.1 10.6 lb.in ± 0.885

Material Specifications	Insulating material	Polyamide	
	Flammability	V0	
	NF F 16 101	I2F2	
Ambient temperature min/max	Service IEC 60068-2-1	-55 +110 °C	-67 +230 F
	Storage	-55 +110 °C	-67 +230 F
	Installing	-5 +40 °C	-23 +104 F

### Ordering Details

#### JB16 Jumper Bars

Description	Type	Order Code	Pack <sup>(nsl)</sup> pieces	Weight g (1 pce)
16 mm 0.630 in spacing	2 poles	<b>JB16-2</b>	<b>1SNK 916 302 R0000</b>	10 10.20
	3 poles	<b>JB16-3</b>	<b>1SNK 916 303 R0000</b>	10 16.00
	5 poles	<b>JB16-5</b>	<b>1SNK 916 305 R0000</b>	10 27.60
	10 poles	<b>JB16-10</b>	<b>1SNK 916 310 R0000</b>	10 56.60

### JB16 Mounting Instructions



- With flat pliers, cut out the partitions on the terminal block insulating body. Be careful to not cut out the jumpered terminal blocks at both ends of the assembly in order to maintain the IP20, Nema1 protection and insulation,
- Install the jumper bar with the recommended tool and torque.